

IEX-16L (74:6B:82:00:A1:23)-v1.34	BACK
IEX-TWO (74:6B:82:00:A1:38)-v1.34	RENAME
IEX-THREE (74:6B:82:00:A1:39)-v1.34	LOCK
	FACTORY DEFAULT
Unit Name PROFILE 5 6 01:00:01 6/28	

In 1.33>

Move cursor to IEX you want to configure.

Press Encoder to access channel configuration

Press Rename to rename the IEX name.

New:

Press Lock to lock the IEX from ANY modification.

If the IEX is locked the softkey reads UNLOCK

Lock/Unlock is only possible when the myMix is connected to IEX through the CONFIGURATION port.

There is no possibility to un/lock over network port.

(If not possible to distinguish the ports then we need a 4-digit Code, 771A the master unlock)

IEX-16L (74:6B:82:00:A1:23)-v1.34	BACK
IEX-TWO (74:6B:82:00:A1:38)-v1.34	RENAME
IEX-THREE (74:6B:82:00:A1:39)-v1.34	UNLOCK
	FACTORY DEFAULT
Unit Name PROFILE 5 6 01:00:01 6/28	

If IEX has been locked nothing can be modified.

Factory Default (only accessible when unlocked), gets to prompt:

Restore Factory default for this IEX16L(Y/N)

Y(es) puts IEX16L to factory default setting (dual mono) names 01 Input1, 02 Input2,